



Kit Includes:

Wreath Plastic
50ct Intelligent Pixels x3
Power Injection End Connector
Power Injection Power Supply

Step 1: Install Lights

From the back (picture to the left shows front view) begin pushing the lights through the corrugated plastic following the path as shown. Always start with the end of the strand with the male plug.

The wreath will use a total of 3 strands, connected end to end. The first 2 strands are powered by the controller. Use the end connector and power supply to inject power to power the last strand.

Step 2: Configure Controllers & Connect Lights

There is timing in WowLights Pro/Pro Plus Christmas sequences for a RGB Wreath on controller ID #23. This can either be shared Pixie 16 controller #15 (shared with Candy Canes, Pixel Stakes, Wreath, and Floods) or a stand-alone Pixie controller #23.

Shared Controller #15: 0001 0101 (Switches 4, 6 & 8 ON, all others OFF) Connect to Output #15

Stand-Alone Controller #23: 0010 0011 (Switches 3, 7 & 8 ON, all others OFF) Connect to Output #1